

AQURA push pears








Push pear with red button and magnetic connector

50.15.0010 per piece

- › Large red call button, with integrated reassurance LED.
- › Finding light to find the push-pear in the dark
- › Flame-retardant and anti-static
- › Connect to the AQURA magnetic sockets 50.12.**** through the self-releasing plug.

Related products:

	Smart single outlet with call and cancellation button	50.12.0030
	Smart double outlet with call and cancellation button	50.12.0040
	Passive single outlet with red button and magnetic socket - 2 relays	50.12.0210
	Passive single outlet with red button and magnetic socket - 4 relays	50.12.0260
	Bracket for push pear mounting	50.09.1500



Push pear with red button, light control and magnetic connector

50.15.0050 per piece

- › Same features as 50.15.0010 with 4 additional buttons.
- › 2 buttons to control lights
 - Room light control
 - Bed light control
- › 2 buttons to control blends, this feature is only available when using outlets 50.12.0260 or 50.12.00xx with 50.11.0010.
 - Blends up control
 - Blends down control

Specifications:

Dimensions (LxWxH)	96 X 59 X 43mm
Material	PE & TPU UL94 Flame retardant
Weight	200gr
IP rating	IP67 (EN60529)
Power consumption	Device standby current: 4,4 mA Device maximum current: 7,3 mA
Compatibility	AQURA magnetic connector Compatible with 50.12.**** outlets
Cable properties	Length : 2,5 meter Diameter : 5,5 mm Color : Pantone 427C
Function buttons	50.15.0010: no extra buttons 50.15.0050: 4 extra buttons
Regulation	CE, RoHS
Mounting	Handheld device, a bracket for wall mounting is provided: 50.09.1500